

* Petrol motors are easier to start

- Normal
- Intensive



Following the principle "who can do more can do less" our most powerful battery boosters can also be convenient for the applications covered by less powerful battery boosters with same voltage of our range.

Caution :

The circumstances/conditions when starting a vehicle depend of various parameters: vehicle's condition, engine type (petrol or diesel) and power, presence of battery in vehicle or not, temperature, frequency of use ... Those influence the jump start's facility. *Chart for your information - Manufacturer's advice.*

TECHNICAL SPECIFICATIONS

Reference	861007
Voltage	12V
Cranking Amps	1600 A
Peak Amps	3875 A
Nr of batteries	1
Starting cable length	1,50 m
Starting cable diameter	35 mm ²
Type of clamps	850 A
Clamps length	215 mm
Clamps opening	54 mm
AC/DC* charger	1,3 A
Cable to charge DC/12V	✔
12V Output	16 A
Reverse polarity signal	●
Internal fuse	500 A
Connector for auxiliary cables	●
Net weight	18 kg
Dimensions (cm)	45 x 13 x 39
Gross weight	20 kg
Packing dimensions (cm)	45 x 17,5 x 51

- ✔ Yes
- ✘ No
- Option
- Upon request

STANDARD EQUIPMENT



LED CLAMPS

The blue clamp is equipped with a led (lamp) for an easier and safer use, especially in the dark.